

Optimized time-dependent perturbation theory for pulse-driven quantum dynamics in atomic or molecular systems

D. Daems*

*Center for Nonlinear Phenomena and Complex Systems,
Université Libre de Bruxelles, CP 231, 1050 Brussels, Belgium*

S. Guérin and H. R. Jauslin

*Laboratoire de Physique de l'Université de Bourgogne,
UMR CNRS 5027, BP 47870, 21078 Dijon, France*

A. Keller and O. Atabek

*Laboratoire de Photophysique Moléculaire du CNRS, Université Paris-Sud,
Bât. 210 - Campus d'Orsay, 91405 Orsay Cedex, France*

(Dated: February 1, 2008)

We present a time-dependent perturbative approach adapted to the treatment of intense pulsed interactions. We show there is a freedom in choosing secular terms and use it to optimize the accuracy of the approximation. We apply this formulation to a unitary superconvergent technique and improve the accuracy by several orders of magnitude with respect to the Magnus expansion.

PACS numbers: 31.15.Md, 03.65.-w, 42.50.Hz

Perturbation theory when combined with a specific treatment for resonances is quite well understood in classical and quantum mechanics for time-independent systems. This includes also time-periodic driven systems for which the periodicity can be treated by Floquet theory in a way that yields a time-independent formulation [1, 2]. One knows that resonances yield divergent terms, that appear as small denominators, which have to be specifically removed. The counterpart of the concept of resonance for time-dependent systems is generally associated to secular terms whose size grows with time (see Ref. [3] and references therein).

With the advent of short ($\simeq 10$ fs) and intense (10^{13} – 10^{15} W/cm²) laser pulses, atomic or molecular systems can be strongly perturbed in a timescale shorter than characteristic times corresponding to the free evolution of the system and adiabatic theories are not applicable (see, e.g., Ref. [4]). The goal of this paper is to formulate a time-dependent perturbation theory well adapted for perturbations localized in time.

The conceptual framework of perturbation theory can be described as follows: The Hamiltonian of the considered system can be decomposed as the sum of two terms $H_1 = H_0 + \epsilon V_1$. The first term H_0 is assumed to have a structure simple enough to lead to explicitly known solutions for its associated propagator $U_{H_0}(t, t_0)$. The term ϵV_1 is supposed to be small with respect to H_0 , in a sense specified below. Time-independent perturbation theories can be equivalently formulated at the level of eigenvectors or operators [5]. A large class of these approaches amounts to construct a unitary transformation T such

that

$$T^\dagger H_1 T = H^e + \epsilon' V', \quad (1)$$

where H^e is still of simple structure [i.e., its propagator $U_{H^e}(t, t_0)$ can be explicitly computed] and $\epsilon' V'$ is a perturbation whose size is smaller than the original one. To compute the transformation T explicitly, one represents it in general either (i) in terms of some power series

$$T = e^{-iW}, \quad W = \sum_k \epsilon^k W_k, \quad (2)$$

or (ii) by an iterative construction as a composition of transformations

$$T = \prod_k e^{-i\epsilon_k W_k}. \quad (3)$$

These procedures generally differ. The former one is referred to as the time-independent Poincaré-Von Zeipel technique, which has been shown to be equivalent to the usual Rayleigh-Schrödinger perturbation theory [6]. The latter procedure includes the Van Vleck technique (for which $\epsilon_k = \epsilon^k$) and the superconvergent Kolmogorov-Arnold-Moser (KAM) expansion (where $\epsilon_k = \epsilon^{2^{k-1}}$ and W_k is ϵ_k -dependent) [7]. The perturbative procedure converges if the remaining perturbation $\epsilon' V'$ can be made to go to zero, as the number of terms in the power series (2) or as the number of compositions in Eq. (3) goes to infinity.

In this description one has to state precisely what class of Hamiltonians H^e can be considered simple. For the first order or the first iteration, one considers $H^e = H_0 + \epsilon D_1$ with the condition that D_1 should be *compatible* with H_0 in the sense that if the propagator of H_0 is known, that of $H_0 + \epsilon D_1$ can also be obtained explicitly. In the

*Electronic address: ddaems@ulb.ac.be

case of time-independent Hamiltonians the condition of compatibility is

$$[H_0, D_1] = 0. \quad (4)$$

For the case of time-dependent Hamiltonians, we show that the condition of compatibility can be generalized to

$$[H_0(t), D_1(t)] = i \frac{\partial D_1}{\partial t}. \quad (5)$$

The construction of transformations of the type of Eq. (2) or (3) involves finding the generator $-i\epsilon W_1(t)$ of the transformation $T_1(t)$, that is the solution to

$$i[W_1(t), H_0(t)] + V_1(t) - D_1(t) = \frac{\partial W_1}{\partial t}. \quad (6)$$

This equation, together with the constraint (5), are usually called *cohomology equations* in the time-independent case [8] and are here generalized to the time-dependent case. These cohomology equations have the same form for higher orders or successive iterations.

Here we formulate the time-dependent perturbation theory by transforming directly the evolution operator instead of considering the perturbed Hamiltonian as is usually done in time-independent theory. We obtain perturbative corrections to the full propagator in the form of a product of propagators which exhibit free parameters appearing through the general solutions of related differential equations. We recover in particular the Magnus expansion [9] as a special case of the time-dependent Poincaré-Von Zeipel theory. This extension also gives the precise correspondence between time-independent resonances and time-dependent secular terms. In the context of pulsed perturbations with a finite duration, the secular terms need not be eliminated. We show the remarkable result that they can be used to improve the convergence of the method at a given order. This optimization is achieved without any *a priori* knowledge of the solution by locating the minimum of a given eigenvalue as a function of the relevant free parameters that are identified. The efficiency of the method is illustrated on a two-level system driven by a short intense pulse.

Perturbation theory, resonances and secular terms. We consider the Hamiltonian $H_1(t) = H_0(t) + \epsilon V_1(t)$, where $H_0(t)$ is associated to a known propagator $U_{H_0}(t, t_0)$. The formulation is presented here for the KAM method, consisting in iterations of transformations which are exactly of the same form at each step. The first iteration involves a unitary operator $T_1(t)$ which transforms the propagator $U_{H_1}(t, t_0)$ according to

$$T_1^\dagger(t) U_{H_1}(t, t_0) T_1(t_0) = U_{H_2}(t, t_0), \quad (7)$$

into a propagator $U_{H_2}(t, t_0)$ associated with the sum $H_2(t)$ of an effective Hamiltonian $H_1^e(t) \equiv H_0(t) + \epsilon D_1(t)$ which contains contributions up to order ϵ and a remainder $\epsilon^2 V_2(t)$. This new propagator, generated by a sum of two Hamiltonians, can be written as the product

$$U_{H_2}(t, t_0) = U_{H_1^e}(t, t_0) R_2(t, t_0), \quad (8)$$

where $R_2(t, t_0)$ satisfies the Schrödinger equation whose Hamiltonian is $\epsilon^2 U_{H_1^e}(t_0, t) V_2(t) U_{H_1^e}(t, t_0)$. Similarly we can factorize $U_{H_1^e}(t, t_0) = U_{H_0}(t, t_0) S_1(t, t_0)$, where $S_1(t, t_0)$ is a unitary operator related to $\epsilon D_1(t)$:

$$i \frac{\partial}{\partial t} S_1(t, t_0) = \epsilon U_{H_0}(t_0, t) D_1(t) U_{H_0}(t, t_0) S_1(t, t_0). \quad (9)$$

The full propagator reads

$$U_{H_1}(t, t_0) = T_1(t) U_{H_0}(t, t_0) S_1(t, t_0) R_2(t, t_0) T_1^\dagger(t_0), \quad (10)$$

which yields the first order KAM approximation for $R_2(t, t_0)$ replaced by the identity. In this construction the only restriction on the self-adjoint operator $\epsilon D_1(t)$ is that it be of order ϵ . Hence we have the freedom to choose the Hamiltonian in Eq. (9) as t -independent, giving

$$D_1(t) = U_{H_0}(t, t_0) D_1(t_0) U_{H_0}(t_0, t), \quad (11)$$

with $D_1(t_0)$ arbitrary, which is the general solution of Eq. (5). This allows one to obtain the solution of Eq. (9) as

$$S_1(t, t_0) = \exp[-i(t - t_0)\epsilon D_1(t_0)]. \quad (12)$$

Differentiating Eq. (10) and substituting $T_1(t) = \exp(-i\epsilon W_1(t))$ leads to Eq. (6). The rest involves a series of k nested commutators that reads $\epsilon^2 V_2(t) = \sum_{k=1}^{\infty} \frac{1}{(k+1)!} i^k \epsilon^{k+1} [W_1(t), \dots [W_1(t), kV_1(t) + D_1(t)] \dots]$. It has exactly the same structure at each iteration which is useful for applications, particularly when high-order computations are needed.

Iterating the time-dependent KAM algorithm reduces the size of the remaining perturbation in a superconvergent way from order $\epsilon^{2^{n-1}}$ to ϵ^{2^n} at step n . The time-dependent Van Vleck technique would allow one to reduce the size of the remainder from order ϵ^n to ϵ^{n+1} . These methods, in the formulation presented here, are unitary upon truncation. The superconvergent character of the KAM algorithm has been shown numerically by applying the method to a two-level system perturbed by a short time-dependent interaction [10].

The *time-independent problem*, i.e., the problem of finding a transformation T_1 that enables one to simplify the time-independent Hamiltonian H_1 according to $T_1^\dagger H T_1 = H_0 + \epsilon D_1 + \epsilon^2 V_2$, is recovered when one conveniently chooses T_1 as time-independent. In this case all the operators, and in particular D_1 and W_1 , are time-independent and the standard cohomology equations are recovered: $[H_0, D_1] = 0$ and $V_1 - D_1 + i[W_1, H_0] = 0$. Their solutions can be determined using the following key property [8]: W_1 exists if and only if $\Pi_{H_0}(D_1 - V_1) = 0$, where Π_{H_0} is the projector in the kernel of the application $A \mapsto [A, H_0]$ (for an operator A acting on the same Hilbert space as H_0). The projector Π_{H_0} applied on an operator A captures thus all the part B of A which commutes with H_0 : $[B, H_0] = 0$. The unique solution D_1 allowing W_1 to exist and satisfying Eq. (4) is thus

$$D_1 = \Pi_{H_0} V_1 \equiv \lim_{T \rightarrow \infty} \frac{1}{T} \int_0^T e^{-itH_0} V_1 e^{itH_0}. \quad (13)$$

The *resonances* are associated with terms of V_1 which commute with H_0 . Application of Eq. (13) can be interpreted as an *averaging* of V_1 with respect to H_0 which allows one to extract resonances.

For the *time-dependent problem*, the general solution of Eq. (6) reads (up to a term $U_{H_0}(t, t_0)B_1U_{H_0}(t_0, t)$ with B_1 any self-adjoint operator that we set here to 0)

$$W_1(t) = \int_{t'_1}^t ds U_{H_0}(t, s) (V_1(s) - D_1(s)) U_{H_0}(s, t), \quad (14)$$

with t'_1 any real number. Defining the average

$$\Pi_- V_1 \equiv \lim_{\tau \rightarrow \infty} \frac{1}{\tau} \int_{t-\tau}^t ds U_{H_0}(t, s) V_1(s) U_{H_0}(s, t), \quad (15)$$

one can show the following property: if $W_1(t)$ is bounded for negative infinite times, then $\Pi_-(V_1 - D_1) = 0$. This is satisfied by $D_1 = \Pi_- V_1$, the only solution compatible with Eqs. (5) and (15). Hence, the averaging $D_1 = \Pi_- V_1$ allows one to remove secular terms at negative infinite times. This gives the precise correspondence between the resonances of stationary problems and the secular terms of time-independent problems. We remark that the definition (15) of the average can be in fact recovered from the formal calculation of the average $\Pi_{K_0} V_1$ [cf. Eq. (13)] with respect to $K_0 = -i\frac{\partial}{\partial t} + H_0$ in an extended space, which includes time as a coordinate [10, 11].

For a pulsed perturbation that is switched on at t_i and off at t_f , Eq. (15) becomes [10] $\Pi_- V_1 = U_{H_0}(t, t_i) V(t_i) U_{H_0}(t_i, t)$. This is a particular solution of Eq. (5) corresponding to the choice $D_1(t_0) \equiv U_{H_0}(t_0, t_i) V(t_i) U_{H_0}(t_i, t_0)$ in Eq. (11). An alternate definition of the average: $\Pi_+ V_1 \equiv \lim_{\tau \rightarrow \infty} \frac{1}{\tau} \int_t^{t+\tau} ds U_{H_0}(t, s) V_1(s) U_{H_0}(s, t)$ gives a different averaging $\Pi_+ V_1 = U_{H_0}(t, t_f) V(t_f) U_{H_0}(t_f, t)$ and allows one to remove secular terms at positive infinite times.

Generally one cannot remove simultaneously the secular terms at negative and positive large times. This shows a conceptual difference between stationary resonances and secular terms associated with perturbations localized in time. Furthermore, it appears that the averaging such as Eq. (15) is not appropriate, but that a definition which combines the two definitions gives a new secular term that could improve the convergence of the algorithm. This suggests to work with the general solution (11) of Eq. (5), written with the perturbation evaluated at a free time t_1 as the arbitrary operator:

$$D_1(t) = U_{H_0}(t, t_1) V_1(t_1) U_{H_0}(t_1, t). \quad (16)$$

The free t_1 can then be chosen to minimize the rest after the first iteration, as we describe below. One has n such free parameters t_k , $k = 1, n$ for n iterations of the KAM algorithm. There is only one such free parameter for the time-dependent Poincaré-Von Zeipel and Van Vleck methods that are order by order techniques. An interesting result is that we recover the Magnus expansion from the time-dependent Poincaré-Von Zeipel in the particular case of $D_k = 0$ and $t'_k = t_0$ for $k = 1, n$.

Optimization of the perturbation theory. After one iteration, the rest $R_2(t, t_0)$ defined in Eq. (8) is associated with a second order operator through $R_2(t, t_0) \equiv e^{-i\epsilon^2 G_2(t)}$ with $G_2(t_0) = 0$. The closer $R_2(t, t_0)$ is to the identity, the smaller the correction terms are, i.e., the more accurate the approximation is. We evaluate the lowest order contribution to $\epsilon^2 G_2(t)$ as

$$\epsilon^2 G_2^{(2)}(t) = \epsilon^2 \int_{t_0}^t du U_{H_1^e}(t_0, u) V_2(u) U_{H_1^e}(u, t_0). \quad (17)$$

It is this operator that has to remain small for the algorithm to converge. The size of an operator A can be characterized by the norm $\|A\| = \sup_{\|\psi\|=1} \|A\psi\|$ with ψ in the appropriate Hilbert space. For an Hermitian matrix this norm reduces to the largest of the absolute values of its eigenvalues.

In order to improve the accuracy we thus seek to minimize $\lambda_2(t)$, the largest of the absolute values of the eigenvalues of $\epsilon^2 G_2^{(2)}(t)$, with respect to the free parameters. To optimize the KAM algorithm, we have at our disposal two free parameters t_k and t'_k at each iteration. We expect the parameters t_k to significantly affect the convergence, as they are related to secular terms.

Perturbation theory for short intense pulses. We consider a system described by the Hamiltonian $\hat{H}$ (autonomous or not) and perturbed by a time-dependent Hamiltonian $\hat{V}(s)$ whose characteristic duration is τ . The perturbation is assumed to satisfy $[\hat{V}(s), \hat{V}(s_0)] = 0$, $\forall s, s_0$ which is realized in many situations of interest. We define a *sudden parameter* ϵ as follows. A dimensionless time t and dimensionless operators H and $V(t)$ are defined through $s \equiv \tau t$, $\hat{H} \equiv \hbar \omega H$, and $\hat{V}(s) \equiv \frac{\hbar}{\tau} V(t)$, leading to the dimensionless Schrödinger equation $i\frac{\partial}{\partial t} U(t, t_0) = \{V(t) + \epsilon H\} U(t, t_0)$, where the sudden parameter is defined as $\epsilon \equiv \omega \tau$. We then apply the perturbation theory described above with the identification $H_0(t) \equiv V(t)$ and $V_1 \equiv H$. This formulation is suited to treat intense short pulses.

Illustration on a pulsed-driven two-level system.

We consider the case where $H_0(t) = \Omega(t)\sigma_1$ and $V_1 = \sigma_3$ with $\Omega(t)$ a pulse that is switched on at t_i and off at t_f , and σ_k the Pauli matrices. Notice that, as discussed above, the role of the perturbation and reference Hamiltonian is interchanged. The pulse area $A \equiv \int_{t_i}^{t_f} \Omega(u) du$ is a dimensionless parameter that can be fixed independently of the sudden parameter ϵ . The error between the numerical solution of the Schrödinger equation at the end of the pulse and the result of n iterations is defined as $\Delta_n \equiv \|U_{H_1}(t_f, t_i) - U_{H_1}^{(n)}(t_f, t_i)\|$. We use the pulse shape $\Omega(t) = 2A \sin^2(\pi t)$ for $0 \leq t \leq 1$, and 0 elsewhere.

The upper panel of Figure 1 shows a comparison of the error Δ_1 for the first order Dyson, first order Magnus and one-iteration KAM methods as a function of t_1 , for a non-perturbative area chosen to produce comparable errors Δ_1 for the Magnus and non-optimized ($t_1 = 0$) KAM techniques. The lower panel displays λ_2 the largest of the




FIG. 1: (a) Common logarithm of the error Δ_1 for the first order Dyson expansion (dashed line), the first order Magnus expansion (dotted line) and the first KAM iteration (solid line); and (b) largest eigenvalue of $\epsilon^2 G_2^{(2)}(t_f)$ as a function of t_1 , for $A = 1$, $\epsilon = 0.5$ and $t_1' = 0$.

absolute values of the eigenvalues of $\epsilon^2 G_2^{(2)}(t_f)$ defined in Eq. (17). We clearly see that the error of the first KAM iteration is correctly estimated by this eigenvalue λ_2 and, in particular, minimized when λ_2 is minimized, i.e., for the value t_1^* . It is worth noting that modifying t_1 covers more than one order of magnitude in the error, a situation that is not restricted to these values of the parameters. The optimized solution provides an improvement of the accuracy by almost one order of magnitude with respect to the Magnus calculation.

Figure 2 displays a comparison of the error Δ_2 for the second order Dyson, second order Magnus and two-iteration KAM methods as a function of t_2 , for $t_1 = t_1^*$. It is seen that the Dyson approach is not applicable in this context of strong field as the second order performs

worse than the first one. Figure 2 also shows that the




FIG. 2: Common logarithm of the error Δ_2 for the second order Dyson expansion (dashed line), the second order Magnus expansion (dotted line) and the second KAM iteration (solid line) with the same parameters as Fig. 1 and $t_1 = t_1^* \approx 0.39$.

second KAM iteration can be enhanced by about two orders of magnitude with an appropriate choice of t_1 and t_2 . This optimized second KAM iteration provides an improvement by two and a half orders of magnitude with respect to the second order Magnus technique. Higher iterations of the KAM technique can also be optimized and produce still better improvement owing to its super-convergent character.

In conclusion, we have presented an optimized perturbation theory for pulse-driven systems, which applies to a wide class of processes controlled by intense femtosecond laser pulses. The optimization reduces to the evaluation of eigenvalues and is therefore easy to implement. We anticipate that this approach will be useful in the context of the laser control of atomic and molecular processes, such as the phase space localisation of Rydberg electron [12], or the alignment and orientation of molecules [4].

This research was supported in part by FNRS, ACI Photonique and Conseil Régional de Bourgogne.

-
- [1] J. C. A. Barata and W. F. Wreszinski, Phys. Rev. Lett. **84**, 2112 (2000).
 - [2] S. Guérin and H. R. Jauslin, Adv. Chem. Phys. **125**, 147 (2003).
 - [3] P. W. Langhoff, S. T. Epstein, and M. Karplus, Rev. Mod. Phys. **44**, 602 (1972).
 - [4] H. Stapelfeldt and T. Seideman, Rev. Mod. Phys. **75**, 543 (2003).
 - [5] H. Primas, Rev. Mod. Phys. **35**, 710 (1963).
 - [6] W. Scherer, J. Phys. A **27**, 8231 (1994).
 - [7] W. Scherer, Phys. Rev. Lett. **74**, 1495 (1995).
 - [8] H. R. Jauslin, S. Guérin and S. Thomas, Physica A **279**, 432 (2000).
 - [9] P. Pechukas and J. C. Light, J. Chem. Phys. **44**, 3897 (1966).
 - [10] D. Daems, A. Keller, S. Guérin, H. R. Jauslin and O. Atabek, Phys. Rev. A **67**, 052505 (2003).
 - [11] W. Scherer, Phys. Lett. A **233**, 1 (1997).
 - [12] D. G. Arbó, C. O. Reinhold, J. Burgdörfer, A. K. Pattnayak, C. L. Stokely, W. Zhao, J. C. Lancaster, and F. B. Dunning, Phys. Rev. A **67**, 063401 (2003).